

PRC100 Coin Counter

This product line represents a very cost-effective concept of coin processing. The PRC 100 is mainly used for counting coins or tokens. It can continuously count (CC) and count to a preset number (PC). The PRC 100 processes pre-sorted coins. The double-knob-adjustment allows simple setup. One setting of the knob is enough to select the proper denomination out of a maximum of 10 different denominations. Coins which are smaller by at least 0.5 mm than the present set denomination are off-sorted automatically. A memory allows the storage of the counted coins.



Detection

Diameter	14-34 mm
Thickness	0.8-3.8 mm
Coin denominations	0-9 (10 types)
Form of counting	CC / PC

Capacity and Speed

Capacity hopper	1000 pcs.
Counting speed	1800-2400 pcs/min

Technical Data

Dimensions (W x L x H)	320 x 225 x 165 mm
Weight	8.8 kg
Power consumption	40 W
Power supply	100-240 V, 50/60 Hz

Last modified : 14.06.06

Specifications are subject to change without notice.
Procoin GmbH 2006.